

Certified Record-High Safety On DMMs

...1kV CAT-IV

Great Electrical Tools With Powerful AutoCheck™ & EF-Detection Features!



BRYMEN[®]
BRIGHT PEOPLE'S CHOICE
<http://www.brymen.com>



**BM680 Professional
DMM Series**



BM685



BM682

BM685	BM682	Functions & Features
●	●	6,000 Counts Large Easy To Read LCD Display
●	●	5/Sec Fast Data Measurement
●	●	Fully Auto-Ranging
●	●	Cat IV 1000V Input Protection On All Functions
●	●	AutoCheck™ Feature (Automatic DCV, ACV & Ohms Selection)
●	●	Non-Contact EF-Detection (NCV)
●	●	Probe-Contact EF Detection For More Precise Indication Of Live
●	●	Intelligent Auto Power Off - Operation & Measurement Reset
●	●	Lo-Z Volts To Drain Ghost Voltages (Auto-VΩ Position)
●	●	Standard Hi-Z Volts To Minimize Loading (V Position)
●	●	1000V Overload-Alert On Volts (Beeps & OL Indication)
●	●	AutoCheck™ Audible Continuity (6kΩ Range)
●	●	AutoCheck™ Ohms 6k Ω To 6M Ω, 4 Ranges (Auto-VΩ Position)
●	●	Ohms 600Ω Range+ Fast Audible Continuity
●	●	Capacitance 100nF To 2000μF, 5 Ranges
●	●	Diode Test
●	●	Range-Lock
●	●	Data Hold
●	●	Fire-Retarded Material Thick Wall Housing
●	●	Over-molded Rubber Holster With Probe Holders
●	●	EMC Meets EN61326, EN61000-4-2 & EN61000-4-3
●	●	Transient Protection Up To 12kV 1.2/50μs Lightning Surge
●	●	UL Classified To IEC61010-1 2nd Ed. CAT IV 1000V AC/DC
●	●	Also UL Listed To UL61010B-1 CAT III 1000V AC/DC

A Leader In DMM Safety... CAT IV 1000V !

Reads Hard Signals Thru Ghost-Voltage-Buster (AutoCheck™) !

Identifies Live Lines By EF-Detection Feature !

DATA HOLD

FREEZES THE DISPLAYING READING FOR LATER VIEW

HIGH SPEED AUTO-RANGING
SHORTENS THE TIME TO TEST AND INCREASES THE EASE OF USE

ASIC TECHNOLOGY
MORE FUNCTIONS & FEATURES AT AFFORDABLE PRICES

LARGE 6000 COUNTS LCD DISPLAY
5/SEC FAST NOMINAL UPDATE RATE

FUNCTION SELECTION

TOGGLE CONVENIENTLY BETWEEN PRIMARY & SECONDARY FUNCTIONS

CAPACITANCE

UP TO 2000 μ F WITH 1000V PROTECTION; AUTO-RANGING

DIODE TEST

FOR CHECKING DIODES AND RECTIFIERS

HIGH IMPEDANCE VOLTAGE

1000VAC/DC MEASURING CAPABILITIES; HIGH INPUT IMPEDANCE FOR LOAD SENSITIVE CIRCUITS

AUTOCHECK™ FEATURE

AUTOMATIC SELECTION OF LoZ DCV, LoZ ACV & OHMS

GHOST-VOLTAGE-BUSTER

LoZ DRAINS GHOST/ STRAY VOLTAGES LEAVING ONLY HARD SIGNALS ON METER READINGS

LVD CAT IV SAFETY

INVESTIGATED BY UL TO IEC61010-1 2ND EDITION CAT IV 1000V AC & DC

EF-DETECTION
BOTH NON-CONTACT & SINGLE-PROBE VOLTAGE DETECTION FOR IDENTIFYING LIVE LINES

AUTO & MANUAL-RANGING
AUTO-RANGING WITH MANUAL-RANGING OVERRIDE

600 OHMS & AUDIBLE CONTINUITY
FOR QUICK OPEN-SHORT TESTS ON SWITCHES, FUSES, AND WIRES

SINGLE HAND OPERATION
CONVENIENTLY LOCATED SWITCH FOR SINGLE HAND OPERATION

INTELLIGENT SLEEP MODE
TO EXTEND BATTERY LIFE

ERGONOMIC STREAMLINE DESIGN
FITS COMFORTABLY IN ONE'S HAND

EMC
MEETS EN61326(1997, 1998/A1), EN61000-4-2(1995), & EN61000-4-3(1996)

RUGGED & DURABLE
HIGH-IMPACT FIRE-RETARDED ENCLOSURE FOR REINFORCED SAFETY & DURABILITY

TRANSIENT PROTECTION
UP TO 12kV 1.2/50 μ s LIGHTNING SURGE; SUPERB PROTECTION FOR SERIOUS USERS

DOUBLE INJECTION HOUSING
OVER-MOLDED BACK WITH HOLDERS FOR PROBE STORAGE AND "THIRD HAND" FEATURE



BM682 & BM685 GENERAL SPECIFICATION

Display: 3-5/6 digits 6,000 counts
Update Rate: 5 per second nominal
Polarity: Automatic
Operating Temperature: -10°C ~ 50°C
Relative Humidity: Maximum relative humidity 80% for temperature up to 31°C decreasing linearly to 50% relative humidity at 50°C
Altitude: Operating below 2000m
Storage Temperature: -30°C ~ 60°C, < 80% R.H. (with battery removed)
Temperature Coefficient:
 Nominal 0.15 x (specified accuracy)/°C @ (-10°C ~ 18°C or 28°C ~ 50°C), or otherwise specified
Sensing: Average sensing on all models

Safety: UL investigated and classified to IEC61010-1 2nd Edition (2001)
Measurement Category: CAT IV 1000V AC & DC
Transient Protection:
 12kV lightning surge (1.2/50µs)
E.M.C.:
 Meets EN61326 (1997, 1998/A1), EN61000-4-2 (1995), & EN61000-4-3 (1996)
 In an RF Field of 3V/m:
 Capacitance function is not specified.
 Other function ranges:
 Total accuracy = Specified accuracy + 4sd
 Performance above 3V/m is not specified.
Overload Protection: 1000VDC & VAC rms

Pollution Degree: 2
Power Consumption: 2mA typical
Power Supply: Single standard 9V battery (NEDA1604, JIS006P, IEC6F22)
Low battery: Below approx. 4.5V
APD Consumption: 2µA typical
APD Timing: Idle for 3 minutes
Low battery: approx. 4.5V
Dimension: L173mm x W83mm x H48.5mm
Weight: approx. 300 gm
Special features: AutoCheck™ (Automatic V & Ω Selection), EF-Detection and Display Hold
Accessories: Test lead pair, Battery installed and User's manual
Optional Accessories: Soft carrying case

BM682 & BM685 Electrical Specification

Accuracy is given as ± (% of reading digits + number of digits) or otherwise specified @ 23°C ± 5°C and less than 75% R.H.

DC Voltage

RANGE	Accuracy	
	BM682	BM685
6000mV ¹⁾	1.3%+2d	0.8%+2d
6.000V	1.3%+2d	0.8%+2d
60.00V	1.3%+1d	0.8%+1d
600.0V	1.2%+4d	1.2%+4d
1000V	1.5%+8d	1.5%+8d

NMRR: > 30dB @ 50Hz/60Hz

CMRR: > 100dB @ DC, 50Hz/60Hz; R_s=1kΩ

Hi-Z DCV (BM685 only) Input Impedance:

5MΩ, 90pF nominal

AutoCheck™ Lo-Z DCV Threshold:

> +1.5VDC & < -1.0VDC nominal

AutoCheck™ Lo-Z DCV Input Impedance:

Initially 4.2kΩ, 90pF nominal;

Impedance increases abruptly within a fraction of a second as display voltage is above 50V (typical). Ended up impedances vs display voltages typically are:

18kΩ @ 100V
 125kΩ @ 300V
 320kΩ @ 600V
 500kΩ @ 1000V

¹⁾Range for BM685 only and can only be entered using RANGE button. Use the 6000mV range for voltage output accessories.

AC Voltage

RANGE	Accuracy	
	BM682	BM685
50Hz ~ 400Hz		
6000mV ¹⁾ , 6.000V, 60.00V	2.5%+3d	1.5%+3d
600.0V	2.5%+6d	2.0%+6d
1000V	2.8%+8d	2.8%+8d

CMRR: > 60dB @ DC to 60Hz, R_s=1kΩ

Hi-Z ACV (BM685 only) Input Impedance:

5MΩ, 90pF nominal

AutoCheck™ Lo-Z ACV Threshold:

> 2VAC (50/60Hz) nominal

AutoCheck™ Lo-Z ACV Input Impedance:

Initially 4.2kΩ, 90pF nominal;

Impedance increases abruptly within a fraction of a second as display voltage is above 50V (typical). Ended up impedances vs display voltages typically are:

18kΩ @ 100V
 125kΩ @ 300V
 320kΩ @ 600V
 460kΩ @ 1000V

¹⁾Range for BM685 only and can only be entered using RANGE button. Use the 6000mV range for voltage output accessories.

Ohms

RANGE	Accuracy ¹⁾	
	BM682	BM685
6.000KΩ ²⁾	0.9%+4d ³⁾	0.9%+4d ³⁾
60.00KΩ	0.9%+4d	0.9%+4d
600.0KΩ	0.9%+1d	0.9%+1d
6.000MΩ	1.2%+4d	1.2%+4d

Open Circuit Voltage: 0.4VDC typical

¹⁾Cool down interval 2 minutes after over 50V measurements in Auto-VΩ position

²⁾Continuity Beeper turns on while < 0.025kΩ

³⁾Add 20d to specified accuracy while reading is below 20% of range

Diode Tester (BM685 only)

Test Current	Open Circuit Voltage
0.25mA typical	< 1.6VDC typical

600Ω with Continuity Beeper (BM685 only)

RANGE	Accuracy
600.0Ω	2.0%+6d ¹⁾

Continuity Beeper Response: < 100µs

Open Circuit Voltage: 0.4VDC typical

Audible Threshold: between 50Ω and 250Ω

¹⁾Add 30d to specified accuracy while reading is below 20% of range.

Capacitance (BM685 only)

RANGE	Accuracy
100.0nF ¹⁾	3.5%+5d
1000nF, 10.00µF, 100.0µF	2.5%+2d
2000µF	2.5%+5d

Accuracies with film capacitor or better.

¹⁾Accuracy below 50nF is not specified.

Non-Contact EF-Detection

Typical Voltage	Bar Graph Indication
15V to 50V	-
30V to 70V	--
50V to 100V	---
70V to 140V	----
above 100V	-----

Indication: Bar graph segments & audible beep tones proportional to the field strength

Detection Frequency: 50/60Hz

Detection Antenna: Top end of the meter

Probe-Contact EF-Detection: For more precise indication of live wires, such as distinguishing between live and ground connections, use the Red (+) test probe for direct contact measurements.



BRYMEN TECHNOLOGY CORPORATION

http://www.brymen.com

TEL: +886 2 2226 3396 (rep)

FAX: +886 2 2225 0025

Copyright © MMIV B.T.C. All rights reserved

Specifications subject to change without notice

Patented & Patents Pending. Printed in Taiwan

REGIONALNE BIURO HANDLOWE
 03-450 WARSZAWA, Ratuszowa 11 pok.68
 tel.: 022 211-13-03; kom. +48 505 107 957
 e-mail: warszawa@biall.com.pl

SIEDZIBA GŁÓWNA, SPRZEDAŻ
 80-174 GDAŃSK, Otomin, Stoleczna 43
 tel.: 058 322-11-91,92; fax: 058 322-11-93
 e-mail: biall@biall.com.pl

